



BuyRailings 71 Commerce Drive Brookfield, CT 06804 T 877-810-4116 F +1-203-930-3620 www.buyrailings.com

A-JB6 Adjust-A-Body® with Hanger Bolt Tensioner Cable For 1/8" Or 3/16" Cable. Use F-4 Ferrule for 1/8" and F-6 Ferrule for 3/16"



Adjust-A-Body® with Hanger Bolt Tensioner
This tensioner screws right into your wooden end post. There is no need for special mounting hardware.



TYPE 316 STAINLESS STEEL

CABLE DIA.	PART NO.	FERRULE NO.	"S"	"T"	"L"	"L1"	"L2"	"L3"	"D"	DRILL SIZE REQUIRED	MINIMUM NOMINAL MEMBER SIZE
1/8"	A-JB6	F-4	5/16"	5/16-24 Lx4	1.10"	2.00"	3.75"	2.75"	5/8"	See NOTE	4 x 4
3/16"	A-JB6	F-4	5/16"	5/16-24 Lx4	1.50"	2.50"	3.75"	2.75"	5/8"	See NOTE	4 x 4
1/4"	A-JB6	F-4	7/16"	7/16-20 Lx4	2.00"	2.50"	4.75"	3.00"	5/8"	See NOTE	4 x 4

*Order Ferrule separately. NOTE: If soft wood (Common Redwood), 7/32" drill bit; if hard wood (Common Douglas Fir), 15/64" drill bit.

- This tensioner screws right into your wooden end post. There is no need for special mounting hardware.
- Require Swaging or Purchase cable with pre-swaged ferrule.
- *Order Ferrule separately. NOTE: If soft wood (Common Redwood), 7/32" drill bit; if hard wood (Common Douglas Fir), 15/64" drill bit. Ferrule Item# are CAF-4, CAF-6 or CAF-8